



SW 1000 BE

Product Data Sheet

The SW 1000 Be is the redesigned version of the Electra Be subwoofer to ensure compatibility with the other loudspeakers in the Sopra line. It is equipped with a 13" (33cm) "W" cone speaker driver and a high-power 600 W RMS BASH® amplifier. The 24-bit digital processor offers a large control panel with settings for adapting the sub to various listening rooms. The SW 1000 Be offers very high performance with a bass cut-off frequency of 18 Hz and an SPL of 118 dB. This model is available in the Black Lacquer finish.

LCD control panel.

13" (33cm) "W" cone speaker driver
High rigidity, no distortion, even at high volumes.



High power 600 W RMS BASH® amplifier
DSP (Digital Signal Processor)
Numerous settings for optimising the subwoofer for the listening room
Several SW 1000 Be subwoofers can be linked up.

Front laminar port.
No dynamic bass compression.

SW1000Be Black Lacquer finish

Key points

- High power amplifier
- Speaker driver developed and manufactured in France by Focal
- Numerous available settings

Standard finish



Black Lacquer

Type	Active bass-reflex subwoofer
Drivers	13" (33cm) "W" woofer
Frequency response (+/-3dB)	20Hz - 150Hz
Low frequency point (-6dB)	18Hz
Subwoofer features	Adjustable LPF: 50Hz to 150Hz (24dB/oct.), 48dB/oct. adjustable subsonic filter, adjustable phase, Boost mode, Night mode, 3 user memories, LFe/Stereo/Digital inputs.
Recommended amplifier power	600W (750W max.) BASH® amplifier
Dimensions (HxWxD)	21 ^{1/16} x19 ^{11/16} x17" (535x500x432mm)
Net weight	92.4lb (42kg)